

Wiring ~ Installation



Install all Handset batteries in the Handsets and connect the power packs to the charging cradles
Place Handsets in charging cradles and charge batteries for 15 hours (1st charge only)
Connect the power pack to the base
Connect the exchange line(s) to the socket(s) on the rear of the base

External calls

Answer a call

Press the **Talk**  button.

Make a call

Press the **Talk**  button and dial the required number **OR**
enter the number to be dialled and press the **Talk**  button

Intercom calls



Answer a call

Press the **Talk**  button.

Make a call

Press the **INT/OK** button.

Register a Handset

On an already registered Handset press **down arrow**  until **BS setting** appears
Press **INT/OK**
Enter the Master PIN (default is 1590)
Press **INT/OK**
Press **down arrow**  until **New HS** appears
Enter Sub PIN (default is 1590)

Press **INT/OK**

Enter the Handset number to registered

Press **INT/OK**

You now have two minutes to complete the following procedure

On the new, unregistered handset press **down arrow**  until **Register** appears

Select the correct base number (if only one base is installed it is base 1)

Handset will search for the base put in registration mode by the above steps

Handset will respond with a number (eg:003aa-001f0h)

Press **INT/OK**

Enter PIN (default is 1590)

Press **INT/OK**

System responds in approx. 5 Secs and Handset returns to idle state with the number displayed on the LCD

Deregister a Handset

NOTE! You cannot use the handset to be deregistered in this procedure

On another registered Handset press down arrow  until **BS setting** appears

Press **INT/OK**

Enter the Master PIN (default is 1590)

Press **INT/OK**

Press down arrow  until **Remove HS** appears

Enter the Handset number to deregistered

Press **INT/OK**

Handset will be deregistered in approx. 5 Secs

DC 209

Product of Aristel Networks Australia

ACN 095 422 450

Unit 1, 25 Howleys Rd.

Notting Hill Victoria

3168

Aristel Networks

Quick Start guide DC 209

**2 Line / 9 Handset
Telephone System**

**Aristel Networks Pty Ltd
Unit 1, 25 Station Street
Notting Hill, Victoria, 3168
Telephone: 03 8542 2300
Facsimile: 03 9544 3299
Version 1.1 January 2003**

